

WORLDWIDE MOTOR CONTROLS

Across-Line Motor Starters - Discount Code: MC2

Definite Purpose Motor Starters



Product Overview

- NEMA 1 enclosure
- Door mounted reset PB standard
- Knockouts for field kits
- Control terminals for field ease
- Large enclosure for wire bends
- Field kits for local start / stop
- Field kits for HOA operation
- 24 VAC and 208 VAC control coil available
- Reset pushbutton supplied standard

ACROSS-LINE
MOTOR STARTERS

HP Rating	Main Voltage	Overload Current Setting	Motor FLA	Auxiliary Contacts	Coil Size	Dimensions (Inches) H x W x D	Box Size	With Main Voltage Coil *		With 120 Volt Coil *	
								Model Number	List Price	Model Number	List Price
Single-Phase - 230 Volt											
1/2	230	4-6	4.9	1NO+1NC	C1	10 x 6 x 4.63	A	WWS0.5-2301P		WWS0.5-2301P-120C	
3/4	230	5-8	6.9	1NO+1NC	C1	10 x 6 x 4.63	A	WWS0.75-2301P		WWS0.75-2301P-120C	
1	230	6-9	8	1NO+1NC	C1	10 x 6 x 4.63	A	WWS1-2301P		WWS1-2301P-120C	
1.5	230	9-13	10	1NO+1NC	C1	10 x 6 x 4.63	A	WWS1.5-2301P		WWS1.5-2301P-120C	
2	230	9-13	12	1NO+1NC	C1	10 x 6 x 4.63	A	WWS2-2301P		WWS2-2301P-120C	
3	230	12-18	17	1NO+1NC	C1	10 x 6 x 4.63	A	WWS3-2301P		WWS3-2301P-120C	
5	230	22-32	28	2NO+2NC	C2	10 x 6 x 4.63	A	WWS5-2301P		WWS5-2301P-120C	
7 1/2	230	34-50	40	2NO+2NC	C3	13.25 x 7.38 x 6.13	B	WWS7.5-2301P		WWS7.5-2301P-120C	
10	230	45-65	50	2NO+2NC	C3	13.25 x 7.38 x 6.13	B	WWS10-2301P		WWS10-2301P-120C	

Accessories / Kits / Parts

Description	Box Size	Model Number	List Price
Start/Stop Pushbutton Kit (Double Headed Style)	A	WWS-SS-A	
Start/Stop Pushbutton Kit (Double Headed Style)	B	WWS-SS-B	
Start/Stop Pushbutton Kit (Double Headed Style)	C	WWS-SS-C	
H-O-A Switch Kit (3 Position)	A	WWS-HOA-A	
H-O-A Switch Kit (3 Position)	B	WWS-HOA-B	
H-O-A Switch Kit (3 Position)	C	WWS-HOA-C	
Replacement Reset Pushbutton Kit	A	WWS-RS-A	
Replacement Reset Pushbutton Kit	B, C	WWS-RS-BC	
AUX 1NO, 1NC	A,B,C	UA-1-11	
Replacement Coils Are Available: 24V / 120V / 208V / 230V / 480V		Please Call	

